

Current Transducer LTS 25-NP

For the electronic measurement of currents: DC, AC, pulsed, mixed with galvanic isolation between the primary circuit (high power) and the secondary circuit (electronic circuit).

$$I_{PN} = 25 \text{ At}$$



Electrical data

I_{PN}	Primary nominal current rms	25	At
I_{PM}	Primary current, measuring range	0 .. ± 80	At
V_{OUT}	Output voltage (Analog) @ I_p	$2.5 \pm (0.625 \cdot I_p / I_{PN}) V$	
	$I_p = 0$	2.5 ¹⁾	V
G	Sensitivity	25	mV/A
N_S	Number of secondary turns (± 0.1 %)	2000	
R_L	Load resistance	≥ 2	kΩ
R_{IM}	Internal measuring resistance (± 0.5 %)	50	Ω
TCR_{IM}	Temperature coefficient of R_{IM}	< 50	ppm/K
V_C	Supply voltage (± 5 %)	5	V
I_C	Current consumption @ $V_C = 5 \text{ V}$	Typ	$28 + I_S^2 + (V_{OUT} / R_L) \text{ mA}$

Accuracy - Dynamic performance data

X	Accuracy @ $I_{PN}, T_A = 25^\circ\text{C}$	± 0.2	%
	Accuracy with R_{IM} @ $I_{PN}, T_A = 25^\circ\text{C}$	± 0.7	%
ϵ_L	Linearity error	< 0.1	%
TCV_{OUT}	Temperature coefficient of V_{OUT} @ $I_p = 0$		
	- 10°C .. + 85°C	Typ 50	Max 100 ppm/K
	- 40°C .. - 10°C		150 ppm/K
TCG	Temperature coefficient of G		
	- 40°C .. + 85°C		50 ³⁾ ppm/K
V_{OM}	Magnetic offset voltage @ $I_p = 0$, after an overload of 3 x I_{PN}		± 0.5 mV
	5 x I_{PN}		± 2.0 mV
	10 x I_{PN}		± 2.0 mV
t_{ra}	Reaction time @ 10 % of I_{PN}	< 100	ns
t_r	Response time to 90 % of I_{PN} step	< 400	ns
di/dt	di/dt accurately followed	> 60	A/μs
BW	Frequency bandwidth (0 .. - 0.5 dB)	DC .. 100	kHz
	(- 0.5 .. 1 dB)	DC .. 200	kHz

General data

T_A	Ambient operating temperature	- 40 .. + 85	°C
T_S	Ambient storage temperature	- 40 .. + 100	°C
m	Mass	10	g
	Standards	EN 50178: 1997	
		IEC 60950-1: 2001	

Notes: ¹⁾ Absolute value @ $T_A = 25^\circ\text{C}$, $2.475 < V_{OUT} < 2.525$

$$\supseteq I_S = I_P / N_S$$

³⁾ Only due to TCR_{IM} .

Features

- Closed loop (compensated) multi-range current transducer using the Hall effect
- Unipolar voltage supply
- Isolated plastic case recognized according to UL 94-V0
- Compact design for PCB mounting
- Incorporated measuring resistance
- Extended measuring range.

Advantages

- Excellent accuracy
- Very good linearity
- Very low temperature drift
- Optimized response time
- Wide frequency bandwidth
- No insertion losses
- High immunity to external interference
- Current overload capability.

Applications

- AC variable speed drives and servo motor drives
- Static converters for DC motor drives
- Battery supplied applications
- Uninterruptible Power Supplies (UPS)
- Switched Mode Power Supplies (SMPS)
- Power supplies for welding applications.

Application domain

- Industrial.

Current Transducer LTS 25-NP

Isolation characteristics

V_d	Rms voltage for AC isolation test, 50 Hz, 1 min	3	kV
\hat{V}_w	Impulse withstand voltage 1.2/50 μ s	> 8	kV
		Min	
V_e	Rms voltage for partial discharge extinction @ 10pC	> 1.5	kV
dCp	Creepage distance ¹⁾	15.5	mm
dCI	Clearance distance ²⁾	6.35	mm
CTI	Comparative Tracking Index (group IIIa)	175	

Notes: ¹⁾ On housing

²⁾ On PCB with soldering pattern UTEC93-703.

Applications examples

According to EN 50178 and IEC 61010-1 standards and following conditions:

- Over voltage category OV 3
- Pollution degree PD2
- Non-uniform field

	EN 50178	IEC 61010-1
dCp, dCI, \hat{V}_w	Rated insulation voltage	Nominal voltage
Single insulation	600 V	600 V
Reinforced insulation	300 V	300 V

Safety



This transducer must be used in electric/electronic equipment with respect to applicable standards and safety requirements in accordance with the manufacturer's operating instructions.



Caution, risk of electrical shock

When operating the transducer, certain parts of the module can carry hazardous voltage (eg. primary busbar, power supply).

Ignoring this warning can lead to injury and/or cause serious damage.

This transducer is a build-in device, whose conducting parts must be inaccessible after installation.

A protective housing or additional shield could be used.

Main supply must be able to be disconnected.

Dimensions LTS 25-NP (in mm.)

Top view dimensions: 22.2 (total width), 12 (to center of pins), 15.2 (to center of secondary pins), 3.5 (to secondary pins), 9.3 (height), 1.8 (width of primary pins).

Side view dimensions: R3.2, R9.2, 1 (width of top), 12.3 (height to secondary pins), 9.5 (height to primary pins), 3x ∅0.5x0.35mm (secondary pins), 3x ∅0.8x0.8mm (primary pins), 2.54 (pin spacing), 1.84 (width of primary pins), 7.62 (width of primary pins).

Detail view dimensions: 3.5 ± 0.03 (height of primary pins), 2.54 (pin spacing), 3.81 (width of primary pins), 12.7 (width of primary pins).

Operation principle

The diagram shows a transformer with primary current i_p and secondary current i_s . The secondary is connected to an operational amplifier circuit with a feedback resistor R_{IM} and a reference voltage V_{Ref} . The output terminals are labeled 0V, 5V, and OUT.

Rep.	Clearance	Creepage
A-B	6.35mm	15.5mm

Number of primary turns	Primary nominal current rms I_{PN} [A]	Nominal output voltage V_{OUT} [V]	Primary resistance R_P [mΩ]	Primary insertion inductance L_P [μH]	Recommended connections
1	± 25	2.5 ± 0.625	0.18	0.013	
2	± 12	2.5 ± 0.600	0.81	0.05	
3	± 8	2.5 ± 0.600	1.62	0.12	

Mechanical characteristics

- General tolerance ± 0.2 mm
- Fastening & connection of primary 6 pins 0.8 x 0.8 mm
Recommended PCB hole 1.3 mm
- Fastening & connection of secondary 3 pins 0.5 x 0.35 mm
Recommended PCB hole 0.8 mm
- Additional primary through-hole ∅ 3.2mm

Remarks

- V_{OUT} swings above 2.5 V when I_P flows from terminals 1, 2, 3 to terminals 6, 5, 4 (with the arrow).
- Temperature of the primary jumper should not exceed 100°C.

Output Voltage - Primary Current

